

A Peer Reviewed Open Access International Journal

An Advanced Control Strategy Based H-Statcom For Power Quality Enhancement



A Deepthi Reddy M.Tech, Department of EPS, Brilliant Engineering College.



K Madhavilatha Assistance Professor, Department of PE, Brilliant Engineering College.



R Nagesh Assistance Professor, Department of PE, Brilliant Engineering College.

ABSTRACT:

The performance of power systems decreases with the size, the loading and the complexity of the networks. This is related to problems with load flow, power oscillations and voltage quality. Such problems are even deepened by thechanging situations resulting from deregulation of the electrical power markets, where contractual power flows do no morefollow the initial design criteria of the existing network configuration. Additional problems can arise in case of large system interconnections, especially when the connecting AC links are weak. FACTS devices, however, provide the necessary featuresto avoid technical problems in the power systems and they increase the transmission efficiency.

This paper presents a studyon the design of a shunt connected FACTS device (STATCOM) and investigates the application of this device to control voltagedynamics and to damp out the oscillation in electric power system. STATCOM is one of the key shunt controllers in flexible alternating current transmission system (FACTS) to control the transmission line voltage and can be used to enhance the load ability of transmission line and extend the voltage stability margin. In this paper, the proposed shunt controller based on thevoltage source converter topology as it is conventionally realized by VSC that can generate controllable current directly at itsoutput terminal.

The performance and behavior of this shunt controller is tested in 3-machine 9-bus system as well as the performance is compared in the test system with and without STATCOM at three cases in MATLAB/Simulink. Simulation results prove that the modeled shunt controller is capable to improve the Power quality significantly.

KEYWORDS:

FACTS, H-STATCOM, VSC, CSC, Cascaded MLI, PLL, Wind Energy, PWM.

I.INTRODUCTION:

The traditional steady state stability studies and Transient stability studies take into account the active power flow P and power angle ∂ and generally assume constant receiving and sending end bus voltage. The reacve power flow Q and voltagefall during heavy current flow is neglected. This approach could not explain the several black-outs in USA, Europe, Japan etc.during the last quarter of the twentieth century. The blackouts were due to voltage collapse. During voltage collapse, the busvoltage starts falling and as a result power transfer P through the transmission line starts reducing resulting in ultimatevoltage collapse and loss of system stability of entire network. That's why voltage stability studies have received moreattention and have acquired a vital place inpower system Studies. Voltage collapse phenomena take place where reactivepower management is inadequate. The application of power electronics in the electric power transmission plays an important role to make the system morereliable, controllable and efficient [1]. Due to deregulation, environmental legislations and cost of construction, it isbecoming increasingly difficult to build new transmission lines. Thus it is essential to fully utilize the capacities of the existingtransmission system. The flexible AC Transmission system (FACTS) has become a popular solution to our large/over extendedpower transmission & distribution system. FACTS devices are proving to be very effective in using the full transmissioncapacity while increasing power system stability, transmission efficiency and maintaining power quality and reliability of Power system.



A Peer Reviewed Open Access International Journal

These devices are mainly based on either voltage source converter (VSC) or Current Source Converter (CSC) and have fast response time. As an important member of FACTS devices family, STATCOM has been at the centre of attention and the subject of active research for many years. STATCOM is a shunt connected device that is used to provide reactivepower compensation to a transmission line. This controller can either absorb or inject reactive power whose capacitive orinductive current can be controlled independent of the AC line voltage. Thus, STAT-COM can enhance the transmission lineload ability by extending the MW margin and improves the oscillation of voltage transients through efficient regulation of thetransmission line voltage at the point of connection [1]-[3]. This paper deals with the modeling of a H-STATCOM with a SPWM based controller implemented on a 3- phase system. The device is connected to a load bus with a converter transformer. The modeling of shunt controller and testingis simulated in the MATLAB/Simulink environment. The controller is represented as block diagram that presents practical electronic model of shunt controller.

WIND ENERGY CONVERSION:

Wind turbines capture power from the wind by means of aerodynamically designed blades and convert it to rotating mechanical power. The number of blades is three in a modern wind turbine. For multi-MW wind turbines the rotational speed is typically 10-15 rpm. The most weight efficient way to convert the low-speed, high-torque power to electrical power is to use a gear-box and a standard generator including a power electronic interface as illustrated in Figure 1.



Fig1.Power conversion stages in a modern wind turbine The gear-box is optional as multi-pole generator systems are also possible solutions. Between the grid and the generator a power converter can be inserted. The electrical output can either be AC or DC.

II.PROPOSED SYSTEM BASIC CONFIG-URATION AND PRINCIPLE OF OPERA-TION:

Cascaded H-Bridges inverter:

A single-phase structure of an m-level cascaded inverter is illustrated in Figure 31.1. Each separate dc source (SDCS) is connected to a single-phase full-bridge, or Hbridge, inverter. Each inverter level can generate three different voltage outputs, +Vdc, 0, and -Vdc by connecting the dc source to the ac output by different combinations of the four switches, S1, S2, S3, and S4. To obtain +Vdc, switches S1 and S4 are turned on, whereas -Vdc can be obtained by turning on switches S2 and S3. By turning on S1 and S2 or S3 and S4, the output voltage is 0. The ac outputs of each of the different full-bridge inverter levels are connected in series such that the synthesized voltage waveform is the sum of the inverter outputs. The number of output phase voltage levels m in a cascade inverter is defined by m = 2s+1, where s is the number of separate dc sources. An example phase voltage waveform for an 11level cascaded H-bridge inverter with 5 SDCSs and 5 full bridges is shown in Figure 31.2. The phase voltage van = va1 + va2 + va3 + va4 + va5.



Fig1: Single Phase Cascaded H-Bridges

The above figure shows for single phase whereas in this proposed system is for 3 phase system.

III.CONTROL STRATEGY:

STATCOM can be controlled in voltage control mode and Var control mode.



A Peer Reviewed Open Access International Journal

The control used in this simulation is ACvoltage control mode. Mainly, the control is divided into two parts. One is for angle order and another is for the order of modulation index. The shunt converter is operated in such a way as to demand this DC terminal power from the line keepingthe voltage across the storage capacitor Vdc constant. So, according to equation-1, the angle is ordered in such a way that the net real power absorbed from the line by this shunt FACTS device is equal to the losses of the converters and thetransformer only. The remaining capacity of this shunt converter can be used to exchange reactive power with the line so toprovide VAR compensation at the connection point. The reactive power according to equation-2 is electronically provided by the shunt converter and the active power is transmitted to the DC terminals. The shunt converter reactive current isautomatically regulated to maintain the transmission line voltage at the point of connection to a reference value.

The line voltage and Dc link voltage across capacitor are measured to calculate the amount of reactive power to regulate line voltage and consequently the modulation index is varied in such a way as to calculate reactive power can be injected the point of connection and thus the shunt FACTS device acts as a voltage regulator. The SPWM firing pulses to the GTOs are obtained by comparing the PWM carrier signal and the reference sine wave. The following figure shows the block diagram of control strategy to generate only one pulse width modulated signal can be generated.



Fig3.voltage levels form example

The above figure shows the example of forming the output voltage levels.

IV.SIMULATION RESULTS:



Fig -4: Extension circuit



Fig .5: Source voltage



Fig 6.Source current



Fig 7.Load voltage



A Peer Reviewed Open Access International Journal



Fig8. Load current





V.CONCLUSION:

In simulation, worst events are considered to examine the performance of modeled shunt connected FACTS device. Thesimulation results show that the modeled STATCOM is capable enough to control the transmission line voltage dynamics aswell as the same shunt controller can be used in VAR control mode. Vdc is regulated by controlling proper phase shift andtransmission voltage is regulated by varying the modulation index. Cascaded H-bridges for 3 phases are used. The response of controller is very fast due to apply direct control method. The simulation results alsoprove that the shunt device with proposed switching scheme functions successfully as the real time voltage controller and itimproves the dynamic stability with a wide range of control.

REFERENCES:

[1] Ye, Y., Kazerani, M., and Quintana, V.H., 2005. Current-source converter. Based STATCOM : Modeling and control. IEEETransactions on Power Delivery 20(2): 795-800.

[2] Jower F.A., 2007, Improvement of synchronizing power and damping power by means of SSSC and STAT-COM: Acomparative study. Electric Power Systems Research 77(8): 1112-1117.

[3] Puleston, P.F., Gonzalez, S.A. and Valenciaga, F., 2007. A STATCOM based variable structure control for power systemoscillations damping. International Journal of Electrical Power & Energy Systems 29(3): 241-250.

[4] Hingorani, N.G. and L. Gyugyi, 2000. Understanding FACTS: Concepts and Technology of Flexible AC Transmission Systems. New York: IEEE Press.

[5] Moran, P.D., Ziogas, L.T., Joos, G. and Hingorani, N.G., 1989. Analysis and design of a three-phase current source solidstate var compensator. IEEE Transactions on Industrial Application 25(2): 356-365.

[6] Gyugyi, L., 1994 Dynamic compensation of AC transmission lines by solid-state synchronous voltage sources. IEEETransactions on power Delivery 9(2): 904-911.

[7] Gyugyi, L., Schauder, C.D., Williams, S.L., Reitman, T.R., Torgerson, D.R., and Edris, A., 1995. The unified power flowcontroller: A new approach to power transmission control. IEEE transactions on power delivery 10(2): 1085-1097.

[8] Lehn, P.W. and M.R. Iravani, 1998. Experimental evaluation of STATCOM closed loop dynamics. IEEE Transactions on Power Delivery 13(4): 1378-1384.

[9] Schauder, C.D. and H. Mehta, 1993. Vector analysis and control of advanced static VAR compensators. IEEE Proceedings 140(4): 299-306.

[10] Sen, K.K., 199. STATCOM-STA Ticsynchronous COM Pensator: Theory, modeling, and O. Farrok. M.G. Rabbani and M.R. Islam/International Energy Journal 11(2010) 43-50.

AUTHOR DETAILS:

A DEEPTHI REDDY

I Received B.Tech degree from PRRM Engineering College, Shabad, RangaReddy, Telangana in 2006. And currently pursuing M.Tech in Electrical power system at Brilliant Grammar School Educational Society's Group of Institutions,RangaReddy, Telangana. Her area of interest is in SCADA and FACTS



A Peer Reviewed Open Access International Journal

K MADHAVILATHA

Obtained her B. Tech (EEE) degree from Sindhura College of Engineering and Technology in 2009, M. Tech (Control Systems) from Malla Reddy Engineering college in 2012. She worked as Asst.Prof. in T R R College of Technology Hyderabad. she has been working as Asst. Prof. in dept. of EEE at Brilliant Grammar School Educational Society's Group of Institutions. Her area of interest includes control systems, electrical machines, HVE, and HVDC. She is having 5 years teaching experience.

R. NAGESH

Obtained his B.Tech (EEE) degree from Vignan Institute of Technology and science in 2010, M.Tech (Power Electronics) from Aurora's Engineering College Bhongir in 2012. He worked as Asst.Prof. in Aurora's Engineering College, Bhongir. He has been working as Asst. Prof. & H.O.D in dept. of EEE at Brilliant Grammar School Educational Society's Group of Institutions. His area of interest includes FACTS devices, electrical machines, and power semiconductor devices. He is having 3 years teaching experience.